2025/10/05 03:28 1/5 Very Shy Robot

# **Very Shy Robot**

Author: Ghibea Ovidiu-Catalin

Group: 1221A

Faculty: FILS

### **Introducere**

This robot has an anxiety problem and does not want to meet with anyoane or anything.

## Descriere generală


Small robot that is capable of sensing incoming obstacles and avoid them. Once the switch is turned on, the robot will start moving in a straight line. The ultrasonic sensor placed on the front of the robot will pick up any incoming waves and will translate this into distance in the code. If the received distance will be lower than a certain threshold He will stop and signal to the motor driver module to turn left until there is nothing in front of him anymore, after which he will continue moving.

### **Hardware Design**

#### Components

Name	Quantity
Arduino Uno	1
HC-SR04 Ultrasonic Sensor	1
Speaker	1
LM298N Motor Driver Module	1
5V DC Motors	2
Switch	1
9V Battery	1
Wheels	2
Chassis	1
Jumper Wires	1

Electric diagram:



### **Software Design**

- Development environments used: ArduinoIDE
- Used libraries:

https://www.arduino.cc/reference/en/libraries/pcm/

#### **How It Works**

First define trig and echo pin of HC-SR04 in the program. In this project the trig pin is connected to GPIO9 and echo pin is connected to GPIO10 of Arduino NANO.

```
int trigPin = 9;  // trig pin of HC-SR04
int echoPin = 10;  // Echo pin of HC-SR04
```

Define pins for input of LM298N Motor Driver Module. The LM298N has 4 data input pins used to control the direction of motor connected to it.

In setup() function, define the data direction of utilised GPIO pins. The four Motor pins and Trig pin is set as OUTPUT and Echo Pin is set as Input.

```
pinMode(revleft4, OUTPUT);
pinMode(fwdleft5, OUTPUT);
pinMode(revright6, OUTPUT);
pinMode(fwdright7, OUTPUT);
pinMode(trigPin, OUTPUT);
// set trig pin as output
```

```
pinMode(echoPin, INPUT);  //set echo pin as input to capture
reflected waves
```

In loop() function, get the distance from HC-SR04 and based on the distance move the motor direction. The distance will show the object distance coming in front of the robot. The Distance is taken by bursting a beam of ultrasonic up to 10 us and receiving it after 10us. To learn more about measuring distance using Ultrasonic sensor and Arduino, follow the link.

```
digitalWrite(trigPin, LOW);
delayMicroseconds(2);
digitalWrite(trigPin, HIGH); // send waves for 10 us
delayMicroseconds(10);
duration = pulseIn(echoPin, HIGH); // receive reflected waves
distance = duration / 58.2; // convert to distance
delay(10);
```

If the distance is greater than the defined distance means there is not obstacle in its path and it will moving in forward direction.

If the distance is less than the defined distance to avoid obstacle means there is some obstacle ahead. So in this situation robot will stop for a while and movebackwards after that again stop for a while and then take turn to another direction.

```
if (distance < 18)</pre>
             digitalWrite(fwdright7, LOW);
             digitalWrite(revright6, LOW);
             digitalWrite(fwdleft5, LOW);
             digitalWrite(revleft4, LOW);
             delay(500);
             digitalWrite(fwdright7, LOW);
                                                 //movebackword
             digitalWrite(revright6, HIGH);
             digitalWrite(fwdleft5, LOW);
             digitalWrite(revleft4, HIGH);
             delay(500);
             digitalWrite(fwdright7, LOW);
                                             //Stop
             digitalWrite(revright6, LOW);
             digitalWrite(fwdleft5, LOW);
             digitalWrite(revleft4, LOW);
             delay(100);
             digitalWrite(fwdright7, HIGH);
```

```
digitalWrite(revright6, LOW);
digitalWrite(revleft4, LOW);
digitalWrite(fwdleft5, LOW);
delay(500);
}
```

This is how a robot can avoid obstacles in its path without getting stuck anywhere.

## **Rezultate Obținute**

Care au fost rezultatele obținute în urma realizării proiectului vostru.

### Concluzii

After finishing the project, I learned that:

- While the code is simple, the hardest part was the making of the chasis.
- Some parts have very tough bolts to unscrew which led to a lot of wasted time
- It was fun to see it work after all the effort put in it

### **Download**

Source Code

**Electric Diagram** 

## Bibliografie/Resurse

- Arduino UNO
- SparkFun Dual H-Bridge motor drivers L298
- SparkFun Ultrasonic Sensor HC-SR04

**Export to PDF** 

From:

http://ocw.cs.pub.ro/courses/ - CS Open CourseWare

Permanent link:

http://ocw.cs.pub.ro/courses/pm/prj2022/robert/mini\_wall-e

Last update: **2022/05/27 17:33** 

